


Notes:

1. Only RoHS Compliant Processes and Materials used for this assembly.
2. Marking to Contain "ConductRF", Part No. & WK/YR Date Code, Black Text.
3. 100% Sweep Test to 18GHz w. factory stored Hi-Point data.



ConductRF(Wk/Yr)
LSA28-S1PF-XXX


Marker Example

Length	XXX	Insertion Loss(dB) Max		
		6GHz	12GHz	18GHz
6"	S06	0.491	0.708	0.879
9"	S09	0.647	0.935	1.163
12"	S12	0.803	1.161	1.446
15"	S15	0.959	1.388	1.730
18"	S18	1.114	1.615	2.014
24"	S24	1.426	2.068	2.581
VSWR(Max)		1.40:1		

Part No. Configurator - XXX

FXX = Length in Feet (eg F03=3ft)
SXX = Length in Inches (eg S18=18")
XXM = Length in Meters (eg 2M5=2.5m)
CXX = Length in CM (eg C50=50cm)

5	Shrink Tube	Marker	White
4	Shrink Tube	Standard	Black
3	Flex 0.086"	A28SS	Blue FEP
2	SMP Female	PPF12B-A28G01	Gold
1	SMA Straight Male	PSM12B-A28G01	Pass. SS
ITEM	DESCRIPTION	MATERIALS	FINISH

					Customer DWG	Title: Low Loss Flex 0.086” SMA Male to SMP Female				
						Remarks:	Originated: 01/27/14	Conduct RF sales@ConductRF.com Tel: +1 978 374 6840	Range: LSA28	
2	Updated SMP to 18GHz version		DG	10/13/17	Dwg Ref: LSA28-S1PF					
1	Pre-Release		DG	01/27/14						
REV.	DESCRIPTION	ECN	DRAWN	DATE	Length Tolerances: ≤24" = ±0.25" >24" = ± 1%	Checked: JW	Approved: PL	Rev: 2	Part No: LSA28-S1PF-XXX	
REVISION HISTORY										