

14-Pin TI Adapter



Overview

The 14-Pin TI Adapter allows connections between J-Link or Flasher and target hardware which use a TI MCU and provides a 14-pin connector (e.g. the BeagleBoard with an OMAP3530 on it), defined by TI. It adapts from the 20-pin 0.1" to a 14-pin 0.1" JTAG connector.

Pin out

TMS	1 ● ● 2	TRST
TDI	3 ● ● 4	GND
VCCS	5 ● ● 6	NC
TDO	7 ● ● 8	GND
RTCK	9 ● ● 10	GND
TCK	11 ● ● 12	GND
EMU0	13 ● ● 14	EMU1

Key features

- Adapts from .1" 20-pin Standard connector to 14-pin TI connector incl. 14-pin cable

Package content

- 14-Pin TI Adapter



Order number

8.06.03